

A

UTILITY PATENT APPLICATION
UNDER 37 CFR 1.53(b)

HONORABLE COMMISSIONER OF
PATENTS AND TRADEMARKS
Washington D.C. 20231

Case Docket No. 041-1987

Sir:

Transmitted herewith for filing is the patent application of:

INVENTOR: Satoshi BAN & Kiyoshi HOTTA
FOR: EARPHONE

Enclosed are:

- [X] 29 pages of specification, claims, abstract
- [X] Declaration & Power of Attorney
- [X] Priority Claimed
- [X] Certified copy of Japanese Patent Application No. 9-001600
- [X] 6 sheets of formal drawing
- [X] An assignment of the invention to MATSUSHITA ELECTRIC INDUSTRIAL CO., LTD.
and the assignment recordation fee
- [X] Return Receipt Postcard
- [] Information Disclosure Statement, Form PTO-1449
- [] Copies of IDS Citations

The filing fee has been calculated as shown below:

(1) FOR	(2) NO. FILED	(3) NO. EXTRA	(4) RATE	(5) AMOUNT
TOTAL CLAIMS	6	-20	0	x \$22.00 = \$0.00
INDEPENDENT CLAIMS	3	-3	0	x \$82.00 = 0.00
MULTIPLE DEPENDENT CLAIM(S) (If applicable)				+ \$270.00 = 00.00
			BASIC FEE	\$ 790.00
Total of above calculations=				\$790.00
[X] Assignment & Recording Fee				<u>\$40.00</u>
TOTAL FEE				\$830.00

- [X] Please charge my Deposit Account No. 12-2237 in the amount of \$ 830.00. A duplicate copy of this sheet is enclosed.
- [X] The Commissioner is hereby authorized to charge payment of the following fees associated with this communication or credit any overpayment to Deposit Account No. 12-2237. A duplicate copy is enclosed.
- [X] Any additional filing fees required under 37 CFR 1.16.

01/07/98
jc494 U.S. PTO

09003812 010798

Docket No.: 041-1987

[X] The Commissioner is hereby authorized to charge payment of following fees during the pendency of this application or credit any overpayment to Deposit Account No. 12-2237. A duplicate copy of this sheet is enclosed.

- [X] Any patent application processing fees under 37 CFR 1.17.
[X] Any filing fees under 37 CFR 1.16 for presentation of extra claims.

LOWE PRICE LEBLANC & BECKER



David J. Serbin
Registration No. 30,589

99 Canal Center Plaza, Suite 300
Alexandria, Virginia 22314
(703) 684-1111 DJS:klm
Date: January 7, 1998

00003812-010798
RECEIVED

- 1 -

TITLE OF THE INVENTION

EARPHONE

BACKGROUND OF THE INVENTION

Field of the Invention

5 This invention relates to an earphone, earphones, or an earphone set for an electric device or devices.

Description of the Related Art

10 There are earphones for audio devices such as CD (compact disc) players, cassette tape players, or radio receivers. There are earphone-microphone combinations for portable communication terminal devices such as portable telephone devices or portable radio communication devices.

15 When one wears earphones for an audio device, one can not effectively hear sounds from an earphone-microphone combination for a portable communication terminal device. Similarly, when one wears an earphone-microphone combination for a portable communication terminal device, one can not effectively hear sounds from earphones for an audio device.

SUMMARY OF THE INVENTION

20 It is an object of this invention to provide an improved earphone, improved earphones, or an improved earphone set.

25 A first aspect of this invention provides an earphone apparatus for an audio device and a portable communication terminal device, comprising a first plug for disconnectable connection with the audio device; a second plug for disconnectable connection with the portable communication terminal device; an electroacoustical

09003812-010798

second plug, the electroacoustical transducer, and the third means for disconnecting the first plug from the electroacoustical transducer and connecting the second plug to the electroacoustical transducer when the level detected by the third means is equal to or higher than a predetermined reference level; fifth means connected to the first plug, the second plug, the electroacoustical transducer, and the third means for disconnecting the second plug from the electroacoustical transducer and connecting the first plug to the electroacoustical transducer in cases where the level detected by the third means drops below the predetermined reference level and then remains lower than the predetermined reference level during longer than a predetermined time length; and sixth means connected to the first plug, the second plug, the electroacoustical transducer, and the third means for holding the first plug disconnected from the electroacoustical transducer and holding the second plug connected to the electroacoustical transducer in cases where the level detected by the third means drops below the predetermined reference level and then remains lower than the predetermined reference level during the predetermined time length or shorter.

A fourth aspect of this invention is based on the first aspect thereof, and provides an earphone apparatus further comprising a microphone element connected to the second plug, and a switch connected to the second plug for generating a control signal transmitted to the portable communication terminal device.

A fifth aspect of this invention is based on the second aspect

05003812.010798

according to a third embodiment of this invention.

Fig. 6 is a perspective view of an earphone-microphone set according to a fourth embodiment of this invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

5

First Embodiment

With reference to Fig. 1, an earphone-microphone set includes a plug 1 for disconnectable connection with a stereophonic audio device (not shown) and a plug 2 for disconnectable connection with a portable communication terminal device (not shown).

10 Examples of the audio device are CD (compact disc) players, cassette tape players, and radio receivers. Examples of the portable communication terminal device are portable telephone devices and portable radio communication devices. The stereophonic audio device may be replaced by a monophonic audio device.

15 The earphone-microphone set also includes a change box 3, a microphone unit 4, and a pair of a left-hand loudspeaker 5A and a right-hand loudspeaker 5B. The plug 1 is connected to the change box 3 via a cable 6. The plug 2 is connected to the change box 3 via a cable 7. The change box 3 is connected to the microphone unit 4 via a cable (no reference numeral). The left-hand loudspeaker 5A is
20 connected to the microphone unit 4 via a cable (no reference numeral). The right-hand loudspeaker 5B is connected to the microphone unit 4 via a cable (no reference numeral).

The change box 3 includes manually-operated volume
25 adjusters or manually-operated variable resistors for controlling the level of an audio signal transmitted from the audio device and the

09003812 010798

control terminal 18C connects with the fixed resistor at a point which can be moved between the ends of the fixed resistor. The first end 18A of the volume adjuster 18 is connected to the right-channel line 11. The second end 18B of the volume adjuster 18 is
5 connected to the reception signal line 13. The control terminal 18C of the volume adjuster 18 is connected to a first terminal of the right-hand loudspeaker 5B via a line extending through the microphone unit 4.

In the change box 3, the ground lines 12 and 16 are
10 connected to each other to form a common ground line 19. The common ground line 19 extends from the change box 3 to second terminals of the left-hand loudspeaker 5A and the right-hand loudspeaker 5B via the microphone unit 4. The transmission signal line 13 and the switch line 15 extend through the change box 3,
15 and reach the microphone unit 4.

The microphone unit 4 includes a microphone element 21 and a manually-operated switch 22. A first terminal of the microphone element 21 is connected to the transmission signal line 14. A second terminal of the microphone element 21 is connected
20 to the common ground line 19. The switch 22 includes first and second terminals. The first and second terminals of the switch 22 are selectively connected to and disconnected from each other in accordance with actuation of a knob of the switch 22. The first terminal of the switch 22 is connected to the switch line 15. The
25 second terminal of the switch 22 is connected to the common ground line 19.

862070-27E0060

The earphone-microphone set of Figs. 1 and 2 operates as follows. The plug 1 is connected to the audio device while the plug 2 is connected to the portable communication terminal device. The left-hand loudspeaker 5A and the right-hand loudspeaker 5B are
5 placed in user's left-hand ear and user's right-hand ear respectively. The portable communication terminal device can change into and out of an earphone mode of operation. During the earphone mode of operation, the portable communication terminal device can output a ring signal or a ring back tone signal which is transmitted along the
10 reception signal line 13.

A left-channel audio signal is transmitted from the audio device to the left-hand loudspeaker 5A via the plug 1, the volume adjuster 17 in the change box 3, and the microphone unit 4. The left-channel audio signal is converted by the left-hand loudspeaker
15 5A into corresponding left-channel sound. The level of the left-channel sound generated by the left-hand loudspeaker 5A is controlled by the volume adjuster 17.

A right-channel audio signal is transmitted from the audio device to the right-hand loudspeaker 5B via the plug 1, the volume
20 adjuster 18 in the change box 3, and the microphone unit 4. The right-channel audio signal is converted by the right-hand loudspeaker 5B into corresponding right-channel sound. The level of the right-channel sound generated by the right-hand loudspeaker 5B is controlled by the volume adjuster 18.

25 The volume control of the left-channel sound from the left-hand loudspeaker 5A and the volume control of the right-channel

sound from the right-hand loudspeaker 5B are linked with each other. As the dial 3a on the change box 3 is rotated in a direction toward a "RADIO CD" side, the levels of the left-channel and right-channel sounds from the left-hand and right-hand loudspeakers 5A and 5B are increased. As the dial 3a on the change box 3 is rotated in a direction away from the "RADIO CD" side, the levels of the left-channel and right-channel sounds from the left-hand and right-hand loudspeakers 5A and 5B are decreased.

When the portable communication terminal device receives an incoming call, the portable communication terminal device outputs a ring signal (a ring back tone signal) which travels along the reception signal line 13. The ring signal is transmitted from the portable communication terminal device to the left-hand and right-hand loudspeakers 5A and 5B via the plug 2, the volume adjusters 17 and 18, and the microphone unit 4. The ring signal is converted by the left-hand and right-hand loudspeakers 5A and 5B into corresponding calling tones. The levels of the calling tones generated by the left-hand and right-hand loudspeakers 5A and 5B are controlled by the volume adjusters 17 and 18. As the dial 3a on the change box 3 is rotated in the direction away from the "RADIO CD" side, the levels of the calling tones from the left-hand and right-hand loudspeakers 5A and 5B are increased. As the dial 3a on the change box 3 is rotated in the direction toward the "RADIO CD" side, the levels of the calling tones from the left-hand and right-hand loudspeakers 5A and 5B are decreased.

The user can hear the calling tones among the left-channel

05003812.010798

hand and right-hand loudspeakers 5A and 5B are controlled by the volume adjusters 17 and 18. As the dial 3a on the change box 3 is rotated in the direction away from the "RADIO CD" side, the levels of the voices from the left-hand and right-hand loudspeakers 5A and 5B are increased. As the dial 3a on the change box 3 is rotated in the direction toward the "RADIO CD" side, the levels of the voices from the left-hand and right-hand loudspeakers 5A and 5B are decreased.

The user can hear the voices of the communication opposite party among the left-channel and right-channel sounds. The level ratio (the volume ratio or the intensity ratio) between the voices of the communication opposite party and the left-channel and right-channel sounds can be varied by the volume adjusters 17 and 18. The volume adjusters 17 and 18 are controlled by actuating the dial 3A. It is preferable that the user actuates the dial 3A to suitably set the level (the volume) of the voices of the communication opposite party relative to the left-channel and right-channel sounds when actuating the switch 22 in response to the calling sounds.

During bidirectional communication, the voice of the user is converted by the microphone element 21 into a corresponding transmission speech signal which travels along the transmission signal line 14. The transmission speech signal is sent from the microphone unit 4 to the portable communication terminal device via the change box 3 and the plug 2. Then, the transmission speech signal is sent from the portable communication terminal device to the communication opposite party.

When the user requires a call, the user actuates the switch 22 in the microphone unit 4 so that the switch 22 generates a call start signal. For example, the user continues to press the switch 22 for a given length of time, and therefore the call start signal is generated.

5 The user may directly operate the portable communication terminal device instead of actuating the switch 22. The call start signal travels along the switch line 15. The call start signal is transmitted from the microphone unit 4 to the portable communication terminal device via the change box 3 and the plug 2. The portable
10 communication terminal device retrieves information of a specified dial number from an internal registration memory in response to the call start signal. The portable communication terminal device transmits a call to an address (a communication opposite party) designated by the specified dial number.

15 Alternatively, a call may be implemented as follows. The switch 22 in the microphone unit 4 is changed between an ON state and an OFF state, and thereby a signal tone is generated by the left-hand and right-hand loudspeakers 5A and 5B. Then, the switch 22 is periodically changed between the ON state and the OFF state a
20 given number of times or for a given length of time, and thereby a control signal is generated which designates one of memorized dial numbers. The control signal is sent from the microphone unit 4 to the portable communication terminal device via the change box 3 and the plug 2. In the portable communication terminal device, one
25 of the memorized dial numbers is designated in response to the control signal. The portable communication terminal device

862070-278E0060

transmits a call to an address (a communication opposite party) corresponding to the designated dial number.

Second Embodiment

Figs. 3 and 4 show an earphone-microphone set which is
5 similar to the earphone-microphone set of Figs. 1 and 2 except that a change box 30 replaces the change box 3 (see Figs. 1 and 2).

The change box 30 includes switches 31, 32, and 33, a level detection circuit 34, and a switch hold circuit 35.

The switch 31 has a first fixed contact 31A, a second fixed
10 contact 31B, and a movable contact 31C. The movable contact 31C is connected to either the first fixed contact 31A or the second fixed contact 31B. When the movable contact 31C is connected to the first fixed contact 31A, the movable contact 31C is disconnected from the second fixed contact 31B. When the movable contact 31C
15 is connected to the second fixed contact 31B, the movable contact 31C is disconnected from the first fixed contact 31A.

The switch 32 has a first fixed contact 32A, a second fixed contact 32B, and a movable contact 32C. The movable contact 32C is connected to either the first fixed contact 32A or the second
20 fixed contact 32B. When the movable contact 32C is connected to the first fixed contact 32A, the movable contact 32C is disconnected from the second fixed contact 32B. When the movable contact 32C is connected to the second fixed contact 32B, the movable contact 32C is disconnected from the first fixed contact 32A.

25 The switches 31 and 32 are ganged. The switches 31 and 32 have a common control terminal. Each of the switches 31 and 32 is

2025 RELEASE UNDER E.O. 14176

changed between two different positions in response to a binary signal applied to the common control terminal. When the movable contact 31C of the switch 31 is connected to the first fixed contact 31A thereof, the movable contact 32C of the switch 32 is connected
5 to the first fixed contact 32A thereof. When the movable contact 31C of the switch 31 is connected to the second fixed contact 31B thereof, the movable contact 32C of the switch 32 is connected to the second fixed contact 32B thereof.

The switch 33 is of the manually-operated type. The switch
10 33 has a first fixed contact 33A, a second fixed contact 33B, and a movable contact 33C. The movable contact 33C is connected to either the first fixed contact 33A or the second fixed contact 33B. When the movable contact 33C is connected to the first fixed contact 33A, the movable contact 33C is disconnected from the
15 second fixed contact 33B. When the movable contact 33C is connected to the second fixed contact 33B, the movable contact 33C is disconnected from the first fixed contact 33A.

The first fixed contact 31A of the switch 31 is connected to the left-channel line 10. The second fixed contact 31B of the
20 switch 31 is connected to the reception signal line 13. The movable contact 31C of the switch 31 is connected to the first terminal of the left-hand loudspeaker 5A via the microphone unit 4. The first fixed contact 32A of the switch 32 is connected to the right-channel line 11. The second fixed contact 32B of the switch
25 32 is connected to the movable contact 33C of the switch 33. The movable contact 32C of the switch 32 is connected to the first

output signal of the switch hold circuit 35 is delayed from the corresponding trailing edge in the output signal of the level detection circuit 34 by a predetermined time length. To this end, the switch hold circuit 35 includes a pulse elongating circuit or a pulse trailing edge delay circuit.

The earphone-microphone set of Figs. 3 and 4 operates as follows. The plug 1 is connected to the audio device while the plug 2 is connected to the portable communication terminal device. The left-hand loudspeaker 5A and the right-hand loudspeaker 5B are placed in user's left-hand ear and user's right-hand ear respectively. Normally, the switch 33 is in a position where the movable contact 33C thereof is connected to the second fixed contact 33B thereof. Normally, the switch 31 is in a position where the movable contact 31C thereof is connected to the first fixed contact 31A thereof. Similarly, the switch 32 is in a position where the movable contact 32C thereof is connected to the first fixed contact 32A thereof.

The portable communication terminal device can change into and out of an earphone mode of operation. During the earphone mode of operation, the portable communication terminal device can output a ring signal or a ring back tone signal which is transmitted along the reception signal line 13.

Under normal conditions, a left-channel audio signal is transmitted from the audio device to the left-hand loudspeaker 5A via the plug 1, the switch 31 in the change box 30, and the microphone unit 4. The left-channel audio signal is converted by the left-hand loudspeaker 5A into corresponding left-channel sound.

In addition, a right-channel audio signal is transmitted from the audio device to the right-hand loudspeaker 5B via the plug 1, the switch 32 in the change box 30, and the microphone unit 4. The right-channel audio signal is converted by the right-hand
5 loudspeaker 5B into corresponding right-channel sound.

When the portable communication terminal device receives an incoming call, the portable communication terminal device outputs a ring signal (a ring back tone signal) which travels along the reception signal line 13 via the plug 2. The ring signal is
10 transmitted from the portable communication terminal device to the switch 31 and the level detection circuit 34 in the change box 30. Also, the ring signal is transmitted to the switch 32 in the change box 30 via the switch 33 therein. Since the ring signal has a level higher than the predetermined reference level, the ring signal
15 is detected by the level detection circuit 34 so that the logic state of the output signal of the level detection circuit 34 changes from the normal state. The logic state of the output signal of the switch hold circuit 35 changes in response to the change in the logic state of the output signal of the level detection circuit 34. When the logic
20 state of the output signal of the switch hold circuit 35 changes, the position of the switch 31 changes so that the movable contact 31C of the switch 31 is disconnected from the first fixed contact 31A thereof and is connected to the second fixed contact 31B thereof. In addition, the position of the switch 32 changes so that the
25 movable contact 32C of the switch 32 is disconnected from the first fixed contact 32A thereof and is connected to the second fixed

09003812.010798
862010.2780060

contact 32B thereof. As a result, the ring signal travels through the switches 31 and 32. On the other hand, the left-channel audio signal and the right-channel audio signal are blocked by the switches 31 and 32 respectively. The ring signal is sent from the change box 30 to the left-hand and right-hand loudspeakers 5A and 5B via the microphone unit 4. The ring signal is converted by the left-hand and right-hand loudspeakers 5A and 5B into corresponding calling tones.

When the user actuates the switch 22 in response to the calling sounds, the switch 22 generates an answer signal which travels along the switch line 15. The user may operate a key on the portable communication terminal device instead of actuating the switch 22. The answer signal is transmitted from the microphone unit 4 to the portable communication terminal device via the change box 30 and the plug 2. The portable communication terminal device takes a suitable step of implementing a terminating connection in response to the answer signal. Also, the portable communication terminal device changes to a bidirectional communication mode of operation in response to the answer signal.

During bidirectional communication, the portable communication terminal device receives a speech signal from the communication opposite party. The portable communication terminal device outputs the reception speech signal which travels along the reception signal line 13 via the plug 2. The reception speech signal is transmitted from the portable communication terminal device to the left-hand and right-hand loudspeakers 5A

862070, 2 FEB 00 50

and 5B via the plug 2, the switches 31, 32, and 33 in the change box 30, and the microphone unit 4. The reception speech signal is converted by the left-hand and right-hand loudspeakers 5A and 5B into corresponding voices. In addition, the reception speech signal is transmitted from the portable communication terminal device to the level detection circuit 34 in the change box 30.

During bidirectional communication, the voice of the user is converted by the microphone element 21 into a corresponding transmission speech signal which travels along the transmission signal line 14. The transmission speech signal is sent from the microphone unit 4 to the portable communication terminal device via the change box 3 and the plug 2. Then, the transmission speech signal is sent from the portable communication terminal device to the communication opposite party.

During bidirectional communication, the level of a signal at the reception signal line 13, that is, the level of the reception speech signal, is monitored by the level detection circuit 34. Since the level of the reception speech signal is higher than the predetermined reference level, the level detection circuit 34 and the switch hold circuit 35 cooperate to keep the switches 31 and 32 in the positions allowing the transmission of the reception speech signal toward the left-hand and right-hand loudspeakers 5A and 5B as long as the reception speech signal is present. In cases where the level of the signal at the reception signal line 13 drops below the predetermined reference level and then continues to be lower than the predetermined reference level during the

the change box 30 in Figs. 3 and 4.

A cable 41 containing the left-channel line 10, the right-channel line 11, and the ground line 12 (see Figs. 2 and 4) extends between the plugs 1 and 43. A cable 42 containing the reception
5 signal line 13, the transmission signal line 14, the switch line 15, and the ground line 16 (see Figs. 2 and 4) extends between the plugs 2 and 44.

The plug 43 can be inserted into the jack 40a to provide connection with the jack 40a. The plug 43 can be removed from
10 the jack 40a to disconnect from the jack 40a. The plug 44 can be inserted into the jack 40b to provide connection with the jack 40b. The plug 44 can be removed from the jack 40b to disconnect from the jack 40b.

The left-channel line 10, the right-channel line 11, and the
15 ground line 12 (see Figs. 2 and 4) in the cable 41 are connected with the change box 40 when the plug 43 is inserted into the jack 40a. The reception signal line 13, the transmission signal line 14, the switch line 15, and the ground line 16 (see Figs. 2 and 4) in the cable 42 are connected with the change box 40 when the plug 44 is
20 inserted into the jack 40b.

Fourth Embodiment

Fig. 6 shows an earphone-microphone set which is similar to the earphone-microphone set of Figs. 1 and 2 or the earphone-microphone set of Figs. 3 and 4 except for design changes explained
25 hereinafter.

The earphone-microphone set in Fig. 6 includes a change box

50 instead of the change box 3 in Figs. 1 and 2 or the change box 30 in Figs. 3 and 4. The body of the change box 50 has a casing and a rotatable reel supported within the casing. The cables 6 and 7 extend into the casing of the change box 50 via an aperture through the casing. Ends of the cables 6 and 7 are connected to the reel in the casing of the change box 50. The cables 6 and 7 can be wound on the reel in the casing of the change box 50. Accordingly, the lengths of the cables 6 and 7 extending outward of the change box 50 can be varied.

Two independent reels may be provided in the change box 50 for the cables 6 and 7 respectively. In this case, the cables 6 and 7 can be independently wound on the respective reels.

Other Embodiments

The earphone-microphone set in Figs. 3 and 4 may be modified to additionally include volume adjusters similar to the volume adjusters 17 and 18 in Fig. 2.

The microphone element 21 and at least one of the left-hand loudspeaker 5A and the right-hand loudspeaker 5B may be in a single unit. In this case, the microphone element 21 is preferably of the bone vibration type.

One of the left-hand and right-hand loudspeakers 5A and 5B may be omitted.

The left-hand and right-hand loudspeakers 5A and 5B may be provided in a headphone or a headset.

The left-hand and right-hand loudspeakers 5A and 5B may be inner earphones.

WHAT IS CLAIMED IS:

1. An earphone apparatus for an audio device and a portable communication terminal device, comprising:
- 5 a first plug for disconnectable connection with the audio device;
- a second plug for disconnectable connection with the portable communication terminal device;
- an electroacoustical transducer connected to the first plug
- 10 and the second plug for converting a first electric signal transmitted via the first plug into corresponding sound, and for converting a second electric signal transmitted via the second plug into corresponding sound; and
- means provided between the first plug and the
- 15 electroacoustical transducer for controlling a level of the first electric signal transmitted to the electroacoustical transducer.
2. An earphone apparatus for an audio device and a portable communication terminal device, comprising:
- 20 a first plug for disconnectable connection with the audio device;
- a second plug for disconnectable connection with the portable communication terminal device;
- an electroacoustical transducer;
- 25 first means connected to the second plug for detecting whether or not a call-related electric signal is outputted from the

09003812.010798
86707028E0060

portable communication terminal device; and

second means connected to the first plug, the second plug, the electroacoustical transducer, and the first means for disconnecting the first plug from the electroacoustical transducer
5 and connecting the second plug to the electroacoustical transducer when the first means detects that a call-related electric signal is outputted from the portable communication terminal device.

3. An earphone apparatus as recited in claim 2, further
10 comprising:

third means connected to the second plug for detecting a level of an electric speech signal outputted from the portable communication terminal device;

fourth means connected to the first plug, the second plug, the
15 electroacoustical transducer, and the third means for disconnecting the first plug from the electroacoustical transducer and connecting the second plug to the electroacoustical transducer when the level detected by the third means is equal to or higher than a predetermined reference level;

20 fifth means connected to the first plug, the second plug, the electroacoustical transducer, and the third means for disconnecting the second plug from the electroacoustical transducer and connecting the first plug to the electroacoustical transducer in cases where the level detected by the third means drops below the
25 predetermined reference level and then remains lower than the predetermined reference level during longer than a predetermined

09003812.010798

an electroacoustical transducer connected to the first plug and the second plug for converting a first electric signal transmitted via the first plug into corresponding sound, and for converting a second electric signal transmitted via the second plug into

5 corresponding sound; and

means provided among the first plug, the second plug, and the electroacoustical transducer for increasing one of levels of the first electric signal and the second electric signal transmitted to the electroacoustical transducer while decreasing the other level.

09003812:010798

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5





FIG. 6



09003812.010798

Docket No.: _____

DECLARATION AND POWER OF ATTORNEY

As a below named inventor, I hereby declare that:

My residence, post office and citizenship are as stated below next to my name,

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter claimed and for which a patent is sought on the invention entitled _____
EARPHONE, the specification of which

[X] is attached hereto [] was filed on _____ as Application Serial No. _____ and was amended on _____ (if applicable)

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is known to me to be material to patentability in accordance with Title 37, Code of Federal Regulations, Section 1.56(a).

I hereby claim foreign priority benefits under Title 35, United States Code, Section 119 of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

Prior Foreign Application(s):			Priority Claimed	
<u>Number</u>	<u>Country</u>	<u>Day/Month/Year filed</u>	<u>Yes</u>	<u>No</u>
9-1600	Japan	January 8, 1997	X	

I hereby claim the benefit under Title 35, United States Code, Section 120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, Section 112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, Section 1.56(a) which occurred between the filing date of the prior application and the national or PCT international filing date of this application:

Prior U. S. Application(s):		
<u>Serial No.</u>	<u>Filing Date</u>	<u>Status: Patented, Pending, Abandoned</u>

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

I hereby appoint the following attorney(s) and/or agent(s): Allan M. Lowe, Reg. No. 19,641; Robert L. Price, Reg. No. 22,685; Stephen A. Becker, Reg. No. 26,527; Robert E. LeBlanc, Reg. No. 17,219; Israel Gopstein, Reg. No. 27,333; Benjamin J. Hauptman, Reg. No. 29,310; Kenneth E. Krosin, Reg. No. 25,735; Frank P. Presta, Reg. No. 19,828; Gilberto M. Villacorta, Reg. No. 34,038; Gene Z. Rubinson, Reg. No. 33,351; Chittaranjan N. Nirmel, Reg. No. 30,408; Keith E. George, Reg. No. 34,111; Christopher W. Brody, Reg. No. 33,613; Arthur J. Steiner, Reg. No. 26,106; Edward J. Wise, Reg. No. 34,523; Alfred A. Stadnicki, Reg. No. 30,226; David L. Stewart, Reg. No. 37,578; John A. Hankins, Reg. No. 32,029; Brian D. Hickman, Reg. No. 35,894; Demetra J. Mills, Reg. No. 34,506; Alexander Yampolsky, Reg. No. 36,324; Timothy R. DeWitt, Reg. No. 35,857; William H. Beha, Reg. No. 38,038; Irah H. Donner, Reg. No. 35,120; Eric J. Kraus, Reg. No. 36,190; Leon R. Turkevich, Reg. No. 34,035; Mark G. Toohey, Reg. No. 35,392; Michael E. McCabe, Jr., Reg. No. 37,182; Edward A. Becker, Reg. No. 37,777; Kenneth M. Berner, Reg. No. 37,093; James H. Meadows, Reg. No. 33,965; and Stephen C. Carlson, Reg. No. 39,929. all of

LOWE, PRICE, LEBLANC & BECKER
99 Canal Center Plaza, Suite 300
Alexandria, Virginia 22314

with full power of substitution and revocation, to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith, and all future correspondence should be addressed to them.

Full name of sole or first inventor: Satoshi Ban

Inventor's signature: *Satoshi Ban*

Date: December 10, 1997

Residence: Osaka, Japan

Citizenship: Japanese

Post Office Address: 5-4-5, Hoshidayamate, Katano-shi, Osaka 576 Japan

Full name of second joint inventor: Kiyoshi Hotta

Inventor's signature: *Kiyoshi Hotta*

Date: December 10, 1997

Residence: Yokohama, Japan

Citizenship: Japanese

Post Office Address: 9-4, Higashi Terao Kitadai, Tsurumi-ku, Yokohama 230 Japan

Full name of third joint inventor:

Inventor's signature:

Date:

Residence:

Citizenship:

Post Office Address: